

# E8231D32N\_LS

## 32A 250V 1 Gang Double Pole Switch with Neon, Lavendar Silver



### Main

|                           |                          |
|---------------------------|--------------------------|
| Range of product          | Pieno                    |
| Product or component type | Switch                   |
| Switch application        | Switch                   |
| Rated current             | 32 A 250 V AC 50 Hz      |
| Local signalling          | Neon                     |
| Number of gangs           | 1 gang                   |
| Load type                 | Fluorescent<br>Resistive |
| Cover frame colour tint   | Lavender silver          |

### Complementary

|                         |  |
|-------------------------|--|
| Wiring device mounting  | Flush<br>Surface                                   |
| Material                | Polycarbonate surround<br>Polycarbonate grid plate |
| Connections - terminals | Pillar terminals                                   |
| Number of cables        | 1 10 mm <sup>2</sup> solid                         |
| Embedding depth         | 23 mm  |
| Width                   | 87 mm  |
| Height                  | 87 mm  |
| Depth                   | 33.8 mm  |

### Environment

|                                       |  |
|---------------------------------------|--|
| Ambient air temperature for operation | -5...40 °C   |
| Relative humidity                     | 0...95 %   |
| Standards                             | BS EN 60669-1<br>GB 16915.1<br>IEC 60669-1<br>MS IEC 60669-1<br>SS 227-1 |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.