



# Tornado T2

## TORNADO 8W CDL E27 220-240V 1PF/6

Tornado has outstanding brightness which makes your colors appear more Vivid. It fits everywhere due to its compact design. With comprehensive product range, it allows easy replacement of incandescent lamps all the way.

### Product data

General Information	
Cap-Base	E27 [ E27]
Nominal Lifetime (Nom)	8000 h
Switching Cycle	5000X
Light Technical	
Color Code	865 [ CCT of 6500K]
Luminous Flux (Nom)	475 lm
Luminous Flux (Rated) (Nom)	475 lm
Color Designation	Cool Daylight
Lumen Maintenance 2000 h (Nom)	85 %
Lumen Maintenance 5000 h (Nom)	75 %
Chromaticity Coordinate X (Nom)	313
Chromaticity Coordinate Y (Nom)	337
Correlated Color Temperature (Nom)	6500 K
Luminous Efficacy (Rated) (Nom)	59 lm/W
Color Rendering Index (Nom)	80
LLMF At End Of Nominal Lifetime (Nom)	70 %
Operating and Electrical	
Input Frequency	50 or 60 Hz
Power (Rated) (Nom)	8 W
Lamp Current (Nom)	60 mA
Wattage Equivalent	40 W

Starting Time (Nom)	0.3 s
Warm Up Time to 60% Light (Min)	5 s
Warm Up Time to 60% Light (Max)	60 s
Power Factor (Nom)	0.6
Voltage (Nom)	220-240 V

### Controls and Dimming

Dimmable	No
----------	----

### Approval and Application

Energy Efficiency Label (EEL)	A
Mercury (Hg) Content (Nom)	1.5 mg
Energy Consumption kWh/1000 h	8 kWh

### Product Data


Full product code	871829121828900
Order product name	TORNADO 8W CDL E27 220-240V 1PF/6
EAN/UPC - Product	8718291218289
Order code	929689868401
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	6
Material Nr. (12NC)	929689868401
Net Weight (Piece)	0.046 kg

# Tornado T2

## Warnings and Safety

- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

## Dimensional drawing



QSPIR-F T2 8W/865 E27 220-240V 50/60Hz

Product	D (max)	C (max)	F (max)
TORNADO 8W CDL E27 220-240V 1PF/6	47.5 mm	86.5 mm	40.5 mm

